

EMERGENCY

BT1000HD FOR REQUIRED EMERGENCY GENERATOR TESTING

BT1000HD is a professional battery & electrical system tester that features a 6/12V batteries / 24V pack test for emergency generators and provides complete test results within one single print out receipt.

BT1000HD FEATURES:

- *Battery, Cranking, & Charging System Tester*
- *24V Pack Test / 6V & 12V Battery Test*
- *12V & 24V Cranking/Charging System Test / IR Test*
- *4 Color LCD Screen Shows Different Colors for Various Test Results*
- *Built-in 2 1/4" Thermal Printer Prints Test Result With Date for Records*
- *Temperature Compensation for Above/Below 0°C (32°F)*
- *Customizable Facility Information on the Printout Test Result*
- *Detachable / Replaceable 10-foot Cable for Easy Replacement*
- *Heavy Duty Casing with Strong and Durable Case Design*
- *Test Code Decoder for Decoding and Saving Test Records*
- *Print Last Result Ability to Directly Print Last Test Result Without Re-testing*
- *12-Month Warranty*



BT1000HD Specifications:

Operating Range:	CCA: 40-2000
Application:	24V Pack Test, 6V & 12V Battery, 12V START-STOP Battery Test, 12V & 24V Cranking/Charging System Test, IR test
Voltage Range:	1V - 31.5V
Battery Types:	Flooded, VRLA/GEL, AGM Flat, AGM Spiral, EFB
Battery Ratings:	CCA/SAE, EN, JIS, DIN, IEC, CA/MCA
Operating Temp:	0° C to 50° C (32° F to 122° F)